
# INSTRUCTION MANUAL

## **Zigbee Push button/Normal Switch Module**

QS-Zigbee-S08-16A-U











#### TECHNICAL SPECIFICATIONS

Product type	Zigbee Push button/Norr Switch Module
Voltage	100-240V AC
Current:	16A
Max. load	3680W/300W for LED
Operation frequency	2.4GHz-2.484GHz IEEE 802.15.4
Operation temp.	-10°C - +40°C
Operation range	≤ 200 m
Dims (WxDxH)	39X39X15 mm
IP rating	IP20
Warranty	2 years
Certificates	CF ROHS

· 🚥







Global international operation Whenever & Wherever You are All-in-one Mobile App



Anywhere Anywhere

Inhouse local operation



U = # 8 # 7 -














Voice control-work Woice control-work Device Sharing with Amazon Alexa

electrician in accordance with local regulations. 2. Keep the device out of reach of children. 3. Keep the device away from water, damp or hot

INSTALLATION


▲ Warnings:



1. Installation must be carried out by a qualified

5. Obstruction by concrete wall or metallic materials may reduce the effective operation range of the device and should be avoided.

6. Do NOT attempt to disassemble repair or modify





### MANUAL OVERRIDE

The switch module terminal reserves the access of manual overide function for the end-user to switch on/off.

• Switch on/off for permanent on/off function.

- 1) Both the adjustment on App and switch can overwrite each other, the last adjustment remains in memory.
- 2) The App control is synchronized with the





Wiring Instructions and Diagrams

- 1. Turn off the power supply before carrying out any
- electrical installation work.
- 2.Connect wires according to the wiring diagram.
- 3.Insert the module into the junction box. 4. Turn on the power supply and follow switch module

- Q1: What should I do if I can't configure the switch
- a. Please check whether device is powered on.
- b. Make sure your mobile and switch module
- are under the same 2.4 Ghz WIFI network.
- c. Whether it's in good internet conditions.
- d. Make sure the password entered in App is correct. e. Make sure the wiring is correct
- O2: What device can be connected to this Zigbee switch

Most of your household electrical appliances can be. such as lamps, laundry machine, coffe maker, etc.



You can still control the device connected the switch module with your traditional switch and once WIFI is active again the device connected to module will connect automatically to your WIFI network.

Q4: What should I do if I change the WIFI network or

change the password? You have to re-connect our Wi-Fi switch module to the

new Wi-Fi network accordingly as per the App User Manual.

- O5: How do I reset the device? 1. Turn on/off manual switch which is connected to the device
- until the indicator light flash guickly.
- 3. Long press the reset key for about 10 seconds until the indicator light flash quickly.

APP USER MANUAL




IOS APP / Android APP





you can also search keyword "Tuya Smart" at App Store or Googleplay to download App.






Log in or register your account with your mobile number or e-mail address. Type in the verification code sent to your mobile or mail box, then set your login password. Click "Create Family" to enter into



Open the control panel of the ZigBee gateway on the App

Before making the reset operation, pls make sure the Zigbee Gateway is added and installed to the WIF1 network. Ensure that the product is within the range of Zigbee Gateway Network.






Turn on/off the manual switch for five times or long press the reset key for about 10seconds until the indicator light on the module flash quickly for pairing.(If you wait more than 180 seconds you need to repeat this passage)



Click "+" (Add sub-device) to select the suitable product gateway and follow the on-screen instruction for paring.



The pairing usually will be finished soon. Pls make your mobile phone and device as close as possible.



When pairing is done, the Zigbee switch will be shown on the App.



Connect to amazon alexa or Google Assistant for voice control, or share the devices with your families or friends.



- WIFI ® Router
- 71. 0
- ZigBee gatewayiPhone, iPad (iOS 7.0 or higher)
- Android 4.0 or higher

